

## LA1608

### 450W 8 Inch Active Party Speaker with DSP Control



#### Description

The LA1608 is an 8-inch active party speaker featuring DSP control, delivering powerful and clear sound with a wide frequency range and high sensitivity. Equipped with an 8-inch woofer and six 2.5-inch tweeters, it offers versatile input options including XLR, 6.35mm, and RCA inputs, as well as a combo input for compatibility with various audio sources. Additionally, it has an XLR output for connecting additional speakers or equipment, and DSP presets for sound customization.

#### Features

- Rated Power: 450W
- 1×8" woofer + 6×2.5" tweeter
- Sensitivity 108dB
- Max. SPL: 118dB
- Frequency Response: 20Hz-250Hz, 250Hz-19kHz
- Allow XLR, 6.35mm, RCA Input, Combo Input and XLR output
- Features Bluetooth connectivity for wireless audio source selection
- Support AC110V/60Hz or AC230V/50Hz power supply

## Specifications

Model	LA1608
Rated Power	450W
LF Woofer	8" Woofer
Tweeter	6pcs*2.5" Driver
Impedance	4Ω
Frequency Range	20Hz-250Hz,250Hz-19kHz
Sensitivity	108dB
Max. SPL	118dB
Audio Source	Bluetooth
Input	XLR, 6.35mm, RCA Input, Combo Input
Output	XLR Output
DSP Presets	MAIN,HIFI,MONITOR,DJ,SPEECH
AC Input	AC110V/60Hz or AC230V/50Hz
G.W	20kg